


LS10 Series Switch Debouncer/Noise-Rejection IC Users Guide



General Description

The LogiSwitch LS10 Series of High Noise Immunity Debouncer/Noise Filter ICs was designed for trouble-free use in the most severe electrically hostile environments.

The LS10 Series of LogiSwitch debouncer/noise filter chips features low-impedance 25 mA totem-pole outputs for each channel. Outputs and inputs are of the same polarity and may be selected for use as active high or active low. The LS10 Series utilizes LogiSwitch's proprietary NoBounce™ technology resulting in a high level of noise immunity. Noise spikes of less than 20 ms duration are prohibited from starting or terminating a cycle.

The input of each channel includes an internal pull-up resistor so the SPST interface requires just one pin (NO or COM) tied to ground and the other to a channel input of the device. All outputs are delayed for a period of 20 ms + bounce time on both activation and release regardless of the bounce duration.

Features


- Eliminates switch bounce
- Utilizes adaptive NoBounce technology
- High level of noise immunity
- Eliminates < 20 ms noise spikes
- Low impedance 25 mA totem pole output/channel
- May be used in 2-position toggle switch On/Off applications

Device Information

Part Number	Channels	Package	Size Information
LS18-P	3	PDIP (8)	Plastic DIP 300 mil
LS18-S	3	SOIC (8)	Narrow SOIC 150 mil
LS19-P	6	PDIP (14)	Plastic DIP 300 mil
LS19-S	6	SOIC (14)	Narrow SOIC 150 mil
LS20-P	9	PDIP (20)	Plastic DIP 300 mil
LS20-S	9	SOIC (20)	Wide SOIC 300 mil


Pin Description LS18

Pin	Name	Function
1	VDD	+2.3 V to +5.5 V Supply Voltage
2	SW0	Normally Open Switch Input 0
3	SW1	Normally Open Switch Input 1
4	SW2	Normally Open Switch Input 2
5	OUT2	Normally Low Output 2
6	OUT1	Normally Low Output 1
7	OUT0	Normally Low Output 0
8	VSS	Ground Reference (Switch Common)




Pin Description LS19

Pin	Name	Function
1	VDD	+2.3 V to +5.5 V Supply Voltage
2	SW0	Normally Open Switch Input 0
3	SW1	Normally Open Switch Input 1
4	SW2	Normally Open Switch Input 2
5	SW3	Normally Open Switch Input 3
6	SW4	Normally Open Switch Input 4
7	SW5	Normally Open Switch Input 5
8	OUT5	Normally Low Output 5
9	OUT4	Normally Low Output 4
10	OUT3	Normally Low Output 3
11	OUT2	Normally Low Output 2
12	OUT1	Normally Low Output 1
13	OUT0	Normally Low Output 0
14	VSS	Ground Reference (Switch Common)



Pin Description LS20

Pin	Name	Function
1	VDD	+2.3 V to +5.5 V Supply
2	SW0	Normally Open Switch
3	SW1	Normally Open Switch
4	SW2	Normally Open Switch
5	SW3	Normally Open Switch
6	SW4	Normally Open Switch
7	SW5	Normally Open Switch
8	SW6	Normally Open Switch
9	SW7	Normally Open Switch
10	SW8	Normally Open Switch
11	OUTS	Normally Low Output 8
12	OUT7	Normally Low Output 7
13	OUT6	Normally Low Output 6
14	OUTS	Normally Low Output 5
15	OUT4	Normally Low Output 4
16	OUT3	Normally Low Output 3
17	OUT2	Normally Low Output 2
18	OUT1	Normally Low Output 1
19	OUT0	Normally Low Output 0
20	VSS	Ground Reference



Simply Plug and Play

The LS10 Series of debouncer chips, like all LogiSwitch products, requires no external clocks, additional components or math calculations based on the particular switch application. ***The LogiSwitch advanced adaptive debounce architecture does it all!***


LS10 Series Timing

Parameter	Min	Typ	Max	Units
t_{bnc} Bounce Time	0	0.2		ms
t_{dbnc} Debounce Time	$t_{dbnc} + t_{cltm}$			
t_{cltm} Clean Time	20	20	20	ms

Electrical Specifications

Parameter	Symbol	Conditions	Min	Typ	Max	Units
Operating Voltage Range	V_{cc}		2.5		5.5	V
Supply Current - LS18	I_{cc}	$V_{cc} = 3.0\text{ V}$, All Inputs Open		1,000	1,550	μA
Supply Current - LS19	I_{cc}	$V_{cc} = 3.0\text{ V}$, All Inputs Open		2.1	2.6	mA
Supply Current - LS20	I_{cc}	$V_{cc} = 3.0\text{ V}$, All Inputs Open		2.1	2.6	mA
Input Pull-up Current per Pin	I_{pu}	LS18	25	100	200	μA
Input Pull-up Current per Pin	I_{pu}	LS19, LS20	25	120	200	μA
Debounce Time	t_{dbnc}	$V_{cc} = 2.5\text{ V to }5.5\text{ V}$		21		ms

Logic Analyzer Capture of a LS10 Series IC Cycle



This logic analyzer capture of a LS10 Series IC cycle showing a noisy switch input commonly applied to all six device channels. Note the initial 19 ms low-going glitch at approximately +780 ms does *not* start a cycle, and the following 18 ms high-going first glitch at about approximately +915 ms does *not* terminate the cycle. LS10 Series devices are designed to function flawlessly in severe electrical environments. These devices reject any uninvited level transition of <20 ms duration.